

Three-axis Joystick Motion Controller, JMC-3-02

Three-axis Pre-wired Joystick with 3 Speed Selection Keys, Quadrature Signal Outputs per Axis

25-pin DB-25, Male Connector

Cable Length = 5.5 ft (168 cm)

PIN	NAME	DESCRIPTION
1		Not Connected
2		Not Connected
3		Not Connected
4		Not Connected
5		Not Connected
6		Not Connected
7	CHA-X	X-axis Channel-A of Quadrature Signal Output
8	CHB-X	X-axis Channel-B of Quadrature Signal Output
9	ENA-X	X-axis Enable Signal Output
10	CHA-Y	Y-axis Channel-A of Quadrature Signal Output
11	CHB-Y	Y-axis Channel-B of Quadrature Signal Output
12	ENA-Y	Y-axis Enable Signal Output
13		Not Connected
14		Not Connected
15		Not Connected
16		Not Connected
17	GND	System Ground
18		Not Connected
19	+5 VDC	+5 VDC Input
20		Not Connected
21		Not Connected
22	CHA-Z	Z-axis Channel-A of Quadrature Signal Output
23	CHB-Z	Z-axis Channel-B of Quadrature Signal Output
24	ENA-Z	Z-axis Enable Signal Output
25		Not Connected



Optimal Engineering Systems, Inc.
6901 Woodley Avenue
Van Nuys, California 91406
U.S.A.

Phone (818) 222-9200
FAX (818) 436-0446
E-mail oes@oesincorp.com
www.oesincorp.com