

Three-axis Joystick Motion Controller, JMC-3-03

Three-axis Pre-wired Joystick with 3 Speed Selection Keys, PWM and Direction Signal Outputs per Axis
25-pin DB-25, Male Connector
Cable Length = 5.5 ft (168 cm)

PIN	NAME	DESCRIPTION
1		Not Connected
2		Not Connected
3		Not Connected
4		Not Connected
5		Not Connected
6		Not Connected
7	DIR-X	X-axis Direction Signal Output
8	PWM-X	X-axis PWM Signal Output
9	ENA-X	X-axis Enable Signal Output
10	DIR-Y	Y-axis Direction Signal Output
11	PWM-Y	Y-axis PWM Signal Output
12	ENA-Y	Y-axis Enable Signal Output
13		Not Connected
14		Not Connected
15		Not Connected
16		Not Connected
17	GND	System Ground
18		Not Connected
19	+5 VDC	+5 VDC Input
20		Not Connected
21		Not Connected
22	PWM-Z	Z-axis PWM Signal Output
23	PWM-Z	Z-axis Direction Signal Output
24	ENA-Z	Z-axis Enable Signal Output
25		Not Connected



Optimal Engineering Systems, Inc.
6901 Woodley Avenue
Van Nuys, California 91406
U.S.A.

Phone (818) 222-9200
FAX (818) 436-0446
E-mail oes@oesincorp.com
www.oesincorp.com